


025

Dimensioni / Dimensions / Abmessungen / Encombres / Dimensiones



- Peso senza motore ~0.7 kg
- Weight without motor ~0.7 kg
- Gewicht ohne Motor ~0.7 kg
- Poids sans moteur ~0.7 kg
- Peso sin motor ~0.7 kg


Per le dimensioni relative alla zona attacco motore (Pm, Dm, bm, tm) fare riferimento alla tabella di pag. 38.

For the dimensions concerning the motor connection area (Pm, Dm, bm, tm) please refer to the table shown at page 38.


Zu den Abmessungen des Motoranschlußflansches (Pm, Dm, bm, tm) siehe Tabelle auf Seite 38.

Pour les dimensions concernant la zone de montage du moteur (Pm, Dm, bm, tm) lire SVP le tableau à la page 38.

Para las magnitudes correspondientes a la zona del motor (Pm, Dm, bm, tm) consulte la tabla de la página 38.




## PAM B5 - Dimensioni / Dimensions / Abmessungen / Encombresments / Dimensiones



B5	IEC										
	056	063	071	080	090	100	112	132	160	180	200
<b>Pm</b>	120	140	160	200	200	250	250	300	350	350	400
<b>Dm</b>	9	11	14	19	24	28	28	38	42	48	55
<b>bm</b>	3	4	5	6	8	8	8	10	12	14	16
<b>tm</b>	10,4	12,8	16,3	21,8	27,3	31,3	31,3	41,3	45,3	51,8	59,3

NMRV (105 ÷ 130) tm= 40,3 (IEC 132)

## PAM B14 - Dimensioni / Dimensions / Abmessungen / Encombresments / Dimensiones



B14	IEC							
	056	063	071	080	090	100	112	132
<b>Pm</b>	80	90	105	120	140	160	160	200
<b>Dm</b>	9	11	14	19	24	28	28	38
<b>bm</b>	3	4	5	6	8	8	8	10
<b>tm</b>	10,4	12,8	16,3	21,8	27,3	31,3	31,3	41,3

NMRV (105 ÷ 130) tm= 40,3 (IEC 132)